

OPTIMA® RedTop F 4,2



Battery Model: RT F 4,2
Part Number: 878 209 000 888 2
Nominal Voltage: 12 volts
NSN: Number applied for
Description: High power, sealed lead acid, engine starting battery

Physical Characteristics

Plate design: High purity lead-tin alloy. Wound cell configuration utilizing proprietary *SPIRALCELL*® technology.
Electrolyte: Sulfuric acid, H₂SO₄
Case: Polypropylene
Color: Case: Dark Gray
Cover: "OPTIMA" Red
Group Size: BCI: 78

	Standard	Metric
Length:	10.018"	254.46 mm
Width:	7.262"	184.45 mm
Height:	7.215"	183.26200 mm (height at the top of the terminals)
Weight:	39.5 lb.	17.9 kg

Terminal Configuration: GM style side terminal (3/8"-16UNC-2B threaded nut).

Performance Data:

Open Circuit Voltage (fully charged): 12.8 volts
Internal Resistance (fully charged): 0.0030 ohms
Capacity: 50 Ah (C/20)
Reserve Capacity: BCI: 100 minutes
(25 amp discharge, 80°F (26.7°C), to 10.5 volts cut-off)

Power:

CCA (EN -18°C): 815 amps
MCA (BCI 0°C): 1000 amps

Recommended Charging:

The following charging methods are recommended to ensure a long battery life:
(Always use a voltage regulated charger with voltage limits set as described below.)

Model: RT F 4,2

These batteries are designed for engine starting applications. They are not recommended or warranted for use in deep cycle applications.

OPTIMA® RedTop F 4,2

Recommended Charging Information:

Alternator:	13.3 to 15.0 volts; no amperage limit
Battery Charger:	13.8 to 15.0 volts; 10 amps maximum; 6-12 hours approximate
Float Charge:	13.2 to 13.8 volts; 1 amp maximum current (indefinite time at lower voltages)
Rapid Recharge: (Constant voltage charger)	Maximum voltage 15.6 volts. No current limit as long as battery temperature remains below 50°C (125°F). Charge until current drops below 1 amp. All limits must be strictly adhered to.

Recharge Time: (example assuming 100% discharge – 10.5 volts)

Current	Approx. time to 90% charge
100 amps	35 minutes
50 amps	75 minutes
25 amps	140 minutes

Recharge time will vary according to temperature and charger characteristics. When using Constant Voltage chargers, amperage will taper down as the battery becomes recharged. When amperage drops below 1 amp, the battery will be close to a full state charge.

(All charge recommendations assume an average room temperature of 25°C, 77°F)

Always wear safety glasses when working with batteries.
Always use a voltage regulated battery charger with limits set to the above ratings.
Overcharging can cause the safety valves to open and battery gases to escape, causing premature end of life. These gases are flammable! You cannot replace water in sealed batteries that have been overcharged. Any battery that becomes very hot while charging should be disconnected immediately.

Not fully charging a battery can result in poor performance and a reduction in capacity.

Shipping and Transportation Information:

OPTIMA batteries can be shipped by AIR. The battery is nonspillable and is tested according to ICAO Technical Instructions DOC. 9284-AN/905 to meet the requirements of Packing Instructions No. 806 and is classified as non-regulated by IATA Special Provision A-48 and A-67 for UN2800. Terminals must be protected from short circuit.

Manufacturing Location:

Enertec Exports S. de R.L. de C.V.
RFC: EEX020516KU2
Avenida. del Parque No. 2155
Monterrey Technology Park
Cienega de Flores, N.L. 65550
MEXICO
Phone: 52 (81) 81542300
Fax: 52 (81) 81542301
BCI = Battery Council International
OPTIMA Batteries
Product Specifications: Model 78
December 2008